



(12) **EUROPEAN PATENT APPLICATION**

(43) Date of publication:
21.02.1996 Bulletin 1996/08

(51) Int Cl.⁶: **G09G 1/16, G06F 3/033**

(21) Application number: **95305410.3**

(22) Date of filing: **02.08.1995**

(84) Designated Contracting States:
DE FR GB NL SE

(30) Priority: **11.08.1994 GB 9416208**
11.08.1994 GB 9416207
11.08.1994 GB 9416269

(71) Applicant:
INTERNATIONAL COMPUTERS LIMITED
Putney, London, SW15 1SW (GB)

(72) Inventors:
• **Liu, Man Cheung**
Wokingham, Berkshire RG11 4PQ (GB)
• **Burton, Sidney**
Reading, Berkshire (GB)

(74) Representative: **Guyatt, Derek Charles et al**
Stevenage, Herts, SG1 2DY (GB)

(54) **Integrated computer and television**

(57) An integrated computer and television system comprises a computer producing an output VGA signal, television circuits for receiving a broadcast television signal and for decoding said signal by analog means to produce an output TV signal, and a monitor having a VGA mode in which it can display VGA signals, and a TV mode in which it can display TV signals, all housed in the same cabinet. A multiplexer is provided, for selecting between the output VGA signal from the computer and the TV signal from the television circuits. The selected signal is fed directly to the monitor, without any analog/digital or digital/analog conversion. The system includes a TV remote control unit. The computer can generate simulated remote control signals for controlling the television circuits, in place of the remote control signals from the remote control unit. The system can also use the remote control unit as a simulated mouse, for controlling movement of a cursor on the computer monitor.




FIG 1

Description

Background to the Invention

This invention relates to an integrated computer and television system.

US patent No. 5192999 describes a multipurpose computerized television in which a television (TV) circuit is housed within the same chassis as a personal computer (PC). The TV signal is converted to digital form, digitally processed, and then stored in a VRAM (video random access memory). The stored TV data can be read out of the VRAM, converted back to analog form, and then displayed on the PC monitor, instead of the PC output. A hand-held remote control unit is used to control both the TV circuit and the PC.

The object of the invention is to provide an improved integrated TV and PC system.

Summary of the Invention

According to the invention there is provided an integrated computer and television system comprising:

- (a) a computer producing an output VGA signal;
- (b) television circuits for receiving a broadcast television signal and for decoding said signal by analog means to produce an output TV signal;
- (c) a monitor having a VGA mode in which it can display VGA signals, and a TV mode in which it can display TV signals; and
- (d) a multiplexer for selecting between said output VGA signal from the computer and said TV signal from the television circuits, for feeding directly to said monitor.

Brief Description of the Drawings

Figure 1 is an overall block circuit diagram of an integrated computer and television system.

Figure 2 is a block diagram of a slot card forming part of the system.

Figure 3 is a block diagram of a TV card forming part of the system.

Description of an Embodiment of the Invention

One embodiment of the invention will now be described by way of example with reference to the accompanying drawings.

As will be described, the embodiment of the invention comprises an integrated multimedia PC (personal computer) and TV (television), housed in a single desktop cabinet, with a VGA (video graphics adaptor) monitor. The system has two modes of operation, referred to

as TV mode and PC mode. An IR (infrared) remote control unit is provided; this has the conventional TV control keys, and in addition has mode control keys, for switching the system between the two modes. In TV mode, a TV picture is displayed on the VGA monitor, and the remote control unit provides the normal TV control functions. Alternatively, the TV can be controlled by signals from the PC, which simulate the IR signals from the remote controller. In PC mode, the VGA monitor displays the computer output, and in this mode the remote control unit can be used as a remote pointing device, instead of the conventional mouse or other pointer device.

Referring to Figure 1, the system comprises a single desktop cabinet 10, including two compartments: a TV compartment 11, and a PC compartment 12. The two compartments are screened from each other, thereby reducing interference between TV and PC circuits in these compartments.

The PC compartment 12 holds a PC motherboard 13, a slot card 14, and an interface ports PCB (printed circuit board) 15.

In this example, the PC motherboard 13 comprises the following:

- 486SX processor running at 33MHz;
- 4 MBytes RAM (random access memory);
- VESA local bus VGA with 1 MByte of VGA RAM;
- a floppy disk interface connected to a 1.44 MByte 3½" floppy disk drive unit 16;
- a fixed disk interface, connected to a 210 MByte IDE fixed disk drive unit 17;
- mouse and keyboard input ports;
- a parallel AT bus port connected to an AT bus 20.

The slot card 14 plugs into the PC motherboard, at right angles to the motherboard, and provides three ISA expansion slots for plugging in expansion PCBs, if required. The slot card also includes a sound processor circuit, a control interface, and a CD ROM interface, connected to a CD ROM drive 21. The slot card will be described in detail later.

The interface ports PCB 15 plugs into the slot card. MIDI (Musical instrument digital interface), joystick, microphone and headphone connectors are mounted on this card.

The TV compartment 11 houses a VGA monitor 22, a front panel PCB 23 and a TV card 24.

The monitor 22 is a conventional VGA monitor with digital control circuits for brightness, contrast and picture size. It is capable of displaying all VGA modes up to 1024X768 non-interlaced, and in addition supports a TV mode capable of displaying both 625 line/50 Hz (PAL)

and 525 line/60 Hz (NTSC) television pictures.

The front panel PCB 23 includes conventional TV control buttons (channel up, channel down, volume up, volume down, program, and store). The TV control signals are fed to the TV card 24. These buttons can also be used as VGA control buttons for controlling the geometry adjustment of the VGA monitor (VGA mode, VGA up, and VGA down). The VGA control signals are fed directly to the VGA monitor 22. The front panel also includes an infrared (IR) receiver, for receiving IR signals from a hand-held remote control unit 25. The IR receiver outputs a remote control signal IRin, which is fed to the slot card 14 and to the TV card 24.

The hand-held remote control unit 25 has conventional keys, including the following:

- numeric keys (numbered 0-9) for channel selection,
- "red", "green", "blue" and "yellow" keys for teletext functions, - picture controls (brightness, contrast, colour),
- sound controls (volume, balance, treble, bass), and
- mute and standby controls.

In addition, the remote control unit has TV and PC keys which can be used for switching the system between the TV mode and the PC mode, as will be described.

The TV card 24 includes a stereo audio power amplifier, TV tuner, IF and decoder circuits, a teletext circuit, and a TV microcontroller. The output of the audio amplifier is fed to internal loudspeakers 26. The TV card also includes a multiplexing circuit, for selecting between the PC VGA signal and the TV signal. The TV card will be described in detail later.

The TV compartment 11 also houses a PC power supply unit 27, for supplying power to the PC compartment, and to the audio amplifier in the TV card. The other circuits in the TV compartment are powered by the PSU in the VGA monitor 22. Both of these PSUs are controlled by a mains on/off switch 28.

Referring to Figure 2, the slot card 14 includes a control interface 31, a CDROM interface 32, an audio mixer 33, and a sound processor circuit 34.

The mixer 33 receives the following signals: microphone input, auxiliary audio input, and the audio output from the CDROM interface 32. The mixer output is fed to the sound processor circuit 34. The sound processor circuit 34 is a standard 16-bit sound processor chip. The output of the sound processor circuit is a stereo audio output signal which is fed to the TV card 24. The sound processor circuit 34 and the CDROM interface 32 both interface with the AT bus from the PC motherboard.

The control interface 31 provides an interface between the AT bus, joystick and MIDI inputs, and the TV card. It comprises an 8-bit input port, and an 8-bit output

port, and includes an interrupt generation circuit. Both ports are I/O mapped, allowing the PC to read or write data to or from these ports over the AT bus.

The output port produces the following signals which are supplied to the TV card:

- I²C out (data and clock): a standard I²C (inter integrated circuit) bus which is used to control the teletext circuit on the TV card.
- TVmute: when true, this mutes the TV sound to the audio amplifier. It is effective only in PC mode, and is ignored in TV mode.
- IRout: a simulated remote control signal which simulates the output of the infrared receiver.
- IRcontrol: this signal is used, as will be described, to control a multiplexer in the TV card which selects the source of the TV control signals. When false, the TV is controlled by the signal IRin from the remote control unit 25, received by the infrared receiver. When true, the TV is controlled by the simulated signal IRout.

The input port receives the following signals:

- I²C in (data and clock): a standard I²C bus, which is used to receive output signals from the teletext circuit.
- IRin: the remote control signal from the IR receiver in the front panel PCB 23.
- STANDBY: when true, indicates that the TV has switched to a standby mode.
- PCmode: when true, indicates that the system has switched into PC mode.

These last two signals (STANDBY and PCmode) both come from the TV microcontroller in the TV card 24.

Referring to Figure 3, this shows the TV card 24 in detail.

The TV card includes conventional analog TV circuits 40 (comprising tuner, IF and analog decoder circuits), a teletext circuit 41, a stereo audio power amplifier 42, and a TV microcontroller 43.

The TV circuits 40 receive broadcast TV signals from an aerial socket, and produce output analog RGB (red, green, blue) and synch signals. The RGB and synch signals are fed to one input of an analog multiplexer 45, the other input of which receives analog VGA signals from the PC motherboard. The multiplexer is controlled by the PCmode signal from the TV microcontroller, such that when PCmode is true, the multiplexer selects the VGA (RGB) signal from the PC, and when PCmode is false, the multiplexer selects the RGB and synch

signals from the TV circuit 40.

The TV circuits 40 also produce stereo audio signals, which are fed to the audio amplifier 42 by way of a muting circuit 46 and a mixer 47. The muting circuit is controlled by the output of an AND gate 48, which receives the TVmute signal from the control interface 31 on the slot card and the PCmode signal from the TV microcontroller. Thus, the TV sound is muted if both TVmute and PCmode are true. The mixer 47 combines the TV audio signal with the audio signal from the sound processor 34 on the slot card.

The teletext circuit 41 is connected to the I²C lines of the control interface 31, allowing it to communicate with the PC.

The TV microcontroller 43 receives control signals from the TV control buttons on the front panel, and also receives control signals from a multiplexer 50. One input of the multiplexer 50 receives the remote control signal IRin from the IR receiver, and the other input receives the simulated remote control signal IRout from the control interface 31 on the slot card. The multiplexer is controlled by the signal IRcontrol from the control interface 31 on the slot card, such that when IRcontrol is false, the signal IRin is selected, and when IRcontrol is true, the signal IRout is selected. In response to the control signals, the microcontroller issues tuning control signals to the TV circuits 40 and issues volume, balance, tone and muting signals to the audio amplifier 42. The microcontroller 43 also generates the STANDBY and PCmode signals referred to above.

The operation of the system in the PC and TV modes will now be described.

PC Mode Operation

In this mode, the multiplexer 45 selects the VGA (RGB) signal from the PC, and so the VGA output from the PC is displayed on the monitor. Any sounds output from the sound processor are fed to the audio amplifier 42 by way of the mixer 47. The TV sound signal is also fed to the mixer 47, unless it is muted by the TVmute signal from the PC.

Also in this mode, the remote control signal IRin from the remote controller can be read by the PC, through the control interface, and this signal can then be used by software in the PC to simulate movement of the mouse or other pointer device, e.g. to control movement of a cursor on the display. More specifically, numeric keys 1-4, 6-9 on the controller are used to simulate mouse movement in one of eight directions, the central numeric key (5) simulates the left mouse button, and numeric key 0 simulates the right mouse button.

In PC mode, the teletext buttons on the remote controller act as control keys (review, stop, play, and fast forward) for the CDROM drive.

The system can be switched into TV mode by pressing the TV selection key on the remote controller.

TV Mode Operation

In this mode, the multiplexer 45 selects the TV signals from the TV circuits 40, and so the TV picture is displayed on the monitor. The TV can be controlled either by using the buttons on the front panel 23, or by using the remote controller 25. Alternatively, the TV can be controlled by software in the PC, using the simulated remote control signal IRout.

The system can be switched into PC mode by pressing the PC key on the remote controller.

It should be noted that in the system described above, digitization of the TV signal, and subsequent conversion back to analog form, is avoided. This reduces cost, and improves TV picture quality.

Claims

1. An integrated computer and television system comprising:
 - (a) a computer (12) producing an output VGA signal;
 - (b) television circuits (40) for receiving a broadcast television signal and for decoding said signal by analog means to produce an output TV signal;
 - (c) a monitor (22) having a VGA mode in which it can display VGA signals, and a TV mode in which it can display TV signals; and
 - (d) multiplexer means (45) for selecting between said output VGA signal from the computer and said TV signal from the television circuits, for feeding directly to said monitor.
2. A system according to Claim 1 wherein said computer, said VGA monitor, and said television circuits are all housed in a single cabinet (10).
3. A system according to Claim 1 or 2 further including remote control means (25) for controlling said television circuits.
4. A system according to Claim 3 wherein said remote control means (25) includes means for switching between a computer mode and a TV mode, and wherein said multiplexer means (45) comprises means operative in said computer mode for selecting said VGA output from the computer, and means operative in said TV mode for selecting the TV signal from said television circuits.
5. An integrated computer and television system comprising:

(a) a computer (12);

(b) television circuits (40) for receiving broadcast television signals;

(c) remote control means (25) for producing remote control signals for controlling said television circuits; and

(d) multiplexer means (50) for selecting simulated remote control signals from said computer for controlling said television circuits, in place of said remote control signals from the remote control means.

5 12. A system according to Claim 11 wherein keys 0 and 5 are used to simulate buttons on said mouse or other pointer device.

6. A system according to Claim 5 wherein said simulated remote control signals are sent to said multiplexer means by way of a computer bus and an I/O mapped control port (31) attached to said bus.

7. A system according to Claim 6 wherein said control port comprises means for generating a control signal for controlling said multiplexer means.

8. A system according to any one of Claims 5 to 7 including TV microcontroller means (43) for controlling said television circuits and means for feeding signals selected by said multiplexer means (50) to said TV microcontroller means.

9. An integrated computer and television system comprising:

(a) a computer (12) having a display monitor (22);

(b) television circuits (40) for receiving broadcast television signals;

(c) remote control means (25) for producing remote control signals for controlling said television circuits;

(d) means (31) for feeding said remote control signals to said computer; and

(e) means for using said signals in the computer to simulate movement of a mouse or other pointer device to control movement of a cursor on said display monitor.

10. A system according to Claim 9 wherein said remote control signals are read by the computer by way of a computer bus and an I/O mapped control port attached to said bus.

11. A system according to Claim 9 or 10 wherein said remote control means includes numeric keys 0-9,

and wherein keys 1-4 and 6-9 are used for simulating movement of a mouse or other pointer device in eight different directions.

10

15

20

25

30

35

40

45

50

55




FIG 1




FIG 2




FIG 3